

Output Functions

This table shows all the outputs and the zone functions and conditions that result in their activation.

Zone Function	Output Functions													
	Bells	Strobe	PA	Intruder	Tamper	Reset	Switch DC	Set	Spare	Ready	Security	AC Fail	Batt Low	
01 Final	S	S	-	S	T	X	-	-	-	A	-	-	-	
02 Exit	S	S	-	S	T	-	-	-	-	A	-	-	-	
03 Intruder	S	S	-	S	T	-	-	-	-	A	-	-	-	
05 Security	S	S	-	S	T	-	-	-	-	A	A	-	-	
07 Entry	S	S	-	S	T	-	-	-	-	A	-	-	-	
08 Push Set	-	-	-	-	T	X	-	-	-	-	-	-	-	
09 Keyswitch	-	-	-	-	T	X	X	S	-	-	-	-	-	
10 Secure Final	S	S	-	S	T	X	-	-	-	A	U	-	-	
11 Part Final	S	S	-	S	T	X	-	-	-	A	-	-	-	
12 Part Entry	S	S	-	S	T	-	-	-	-	A	-	-	-	
13 PA	A	A	A	-	T	-	-	-	-	A	-	-	-	
14 PA Silent	-	-	A	-	T	-	-	-	-	A	-	-	-	
15 PA Delay	A	A	A	-	T	-	-	-	-	A	-	-	-	
16 PA Delay Silent	-	-	A	-	T	-	-	-	-	A	-	-	-	
18 Spare	-	-	-	-	T	-	-	-	-	-	-	-	-	
19 Fire	A	A	-	-	T	-	-	-	-	-	-	-	-	
20 Tamper	S	S	-	S	A	-	-	-	-	A	-	-	-	
22 Beam Pair	S	S	-	S	T	-	-	-	-	A	-	-	-	
23 Battery Low	-	-	-	-	T	-	-	-	-	-	-	-	U	
24 Line Fail	-	-	-	-	T	-	-	-	-	-	-	-	-	
25 AC Fail	-	-	-	-	T	-	-	-	-	-	-	A	-	
26 Log	-	-	-	-	T	-	-	-	-	A	-	-	-	
28 Video	S	S	-	S	T	-	-	-	-	A	-	-	-	
29 Video Exit	S	S	-	S	T	-	-	-	-	A	-	-	-	
32 Set Log	-	-	-	-	T	-	-	-	-	-	-	-	-	
33 Custom-A	?	?	?	?	?T	?	?	?	?	?	?	?	?	
34 Custom-B	?	?	?	?	?T	?	?	?	?	?	?	?	?	
39 Keyswitch Reset	-	-	-	-	T	X	-	-	-	-	-	-	-	
40 Bell fail	-	-	-	-	-	-	-	-	-	-	-	-	-	
41 Intr Low	S	S	-	S	T	-	-	-	-	A	-	-	-	
42 Intr High	S	S	-	S	T	-	-	-	-	A	-	-	-	
43 PSU Fault	-	-	-	-	T	-	-	-	-	-	-	-	-	
44 Fault	-	-	-	-	T	-	-	-	-	-	-	-	-	
45 Entry 2	S	S	-	S	T	-	-	-	-	A	-	-	-	
53 Monitor	-	-	-	-	-	-	-	-	-	-	-	-	-	

Key:

- S** Activates when system is Set
- P** Activates when system is Part Set
- U** Unset
- A** Activated in any condition
- No effect
- O** Activates when zone is omitted
- ?** Activation dependant on system programming
- X** Activates during Exit Time
- E** Activates during Entry Time
- L** Switches output off if linked to destination output
- T** Activates if zone resistance is less than value for tamper s/c or greater than value for tamper o/c